

# GEORIX Multi-Constellation Single-Frequency GNSS Receiver

GEORIX, the RUAG Space multi-constellation (GPS, GALILEO) single-frequency GNSS Receiver for GTO and GEO applications provides an excellent on-board real-time navigation solution accuracy of below 20 meter (in GEO).



## KEY FEATURES

- Antenna with gain pattern optimised for GEO
- Detached LNAs for improved performance figures
- GTO support, e.g. for electric propulsion satellites
- Support for cross-coupling of two non-redundant antenna/LNA sets to cold-redundant electronics box
- Accurate force model-based orbit propagator
- Advanced Kalman filtering allows high on-board navigation performance
- Flexible acquisition and tracking concept providing:
  - Single frequency signal processing of up to 12 satellites
  - Sliding search window for minimized acquisition times
  - Doppler-based loop aiding
- Configurable data rate per measurement type
- Autonomous start-mode determination for minimized time-to-first-fix
- Powerful parameter interface supports changes in standby and operational mode
- Additional data products provide excellent visibility of receiver internals
- Low mass and power consumption

**RUAG Space | Product Group Electronics**

[sales.electronics.usa@ruag.com](mailto:sales.electronics.usa@ruag.com)

[sales.electronics.europe@ruag.com](mailto:sales.electronics.europe@ruag.com)

[www.ruag.com/space](http://www.ruag.com/space)

**Together  
ahead. RUAG**

## Supported GNSS Signals

Based on dedicated RF- and Mixed-Signal ASICs as well as the AGGA-4 ASIC, GEORIX is able to use the following signals:

- GPS C/A on L1
- Galileo E1 B/C

## On-board Navigation Solution Accuracy in GEO

- Position: 20.0 m 3D rms
- Velocity: 1 cm/s 3D rms
- Time offset 1PPS ( $1\sigma$ ): < 0.5  $\mu$ s

## Time to first fix

- Warm start < 15 min (in GEO)

## Physical / Environment

### LNA:

- Size: 168x54x80 mm<sup>3</sup> ; Weight: 0.6 kg

### Electronic box:

- Size: 286x201x226 mm<sup>3</sup> ; Weight: 9.0 kg
- Operating temperature: -30° C to +60° C (qualification level)
- Minimum switch-on temperature: -40° C (qualification level)
- Radiation: suitable for GTO (200 days) and GEO (15 years)
- Power consumption: 15 W avg.

### Antenna (recommended for GEO):

- Patch Excited Cup antenna
- Size: Ø 212 mm, h: 179 mm ; weight: 548 g

## Data Products

- Navigation solution based on GPS/GALILEO constellations
- PPS signal synchronized to GPS/GALILEO second
- Carrier phase measurements for each tracked signal
- Code phase measurements for each tracked signal
- Support data:
  - Tracking state
  - GDOP
  - Carrier to noise (C/N) measurement of each tracked signal
  - Noise measurements of each RF down-conversion chain
  - Satellites in view status
  - Satellite navigation message

## Interfaces

- TC/TM: MIL-STD-1553B or UART (RS-422) or SpaceWire
- PPS output nom/red/test (RS-422)
- Primary power input 100 V regulated
- ON/OFF high level command interface
- Thermistor TM interfaces

## Programs/Heritage

RUAG has delivered 22 flight models of the heritage receiver, a GPS Precise Orbit Determination Receiver based on AGGA-2 and LEON ASICs for:

- Swarm earth-observation mission of ESA, based on three satellites flying in formation with a common launch in 2013
- Sentinel-1, Sentinel-2 and Sentinel-3 A/B satellites of ESA's and the European Commission's Copernicus program (6 satellites)
- ESA/JAXA mission Earthcare
- NASA's mission ICESat-2

From the heritage receivers 20 out of 22 delivered flight models have been launched and are functioning flawlessly in orbit to the full satisfaction of the customers.

From the successor GNSS receiver family (PODRIX, LEORIX and GEORIX) more than 40 flight models have already been delivered to the international customers.